

# Network I/O mixing breakout box Dante™/AES67 - 4 x Mic/Line outputs

### Highlights:

- · All-in-one mixing & sound processing
- 4 x 4 channels Dante<sup>™</sup> & AES67
- 4 x Mic/Line outputs
- Integrated Bluetooth receiver (Version 4.2)
- · Compatible with BAE100 extender kit for a higher gain and reception range
- S-box™ modular multifunctional enclosure



NIO series are Dante™/AES67 network I/O mixing breakout boxes featuring terminal block input and output audio and Bluetooth connections. The audio inputs can be switched between line-level and microphone-level audio signals and phantom power (+48 V DC) can be applied to the input connectors for powering condenser microphones.

Various further integrated DSP functions such as EQ, automatic gain control, and other device settings can be configured through the AUDAC Touch™. The IP-based communication makes it future-proof while also being backwards compatible with many existing products.

The NIO series is compatible with any PoE network-based installation thanks to the limited PoE power consumption. The networked I/O expanders are compatible with MBS1xx setup box installation accessories which allow them to be mounted under a desk, in a closet, on the wall, on top of a dropped ceiling or a 19" equipment rack.

#### Applications:

- Retail
- Education
- Corporate
- Hotels
- · Bars & Restaurants
- · Sporting facilities





#### Certification:





#### Properties:



(m) Internal mixing & EQ

# Additional Inputs:



\* Bluetooth

# System specifications:

| Inputs        | Туре                  | Bluetooth receiver (Version 4.2)                |
|---------------|-----------------------|---|
|               |                       | Dante™/AES67 (4 channels)                       |
|               |                       | RJ45 (With indicator LED's)                     |
|               | Impedance             | 10 kΩ Unbalanced                                |
|               |                       | 20 kΩ balanced                                  |
|               | Configurable Settings | Gain  |
|               |                       | AGC   |
|               |                       | Maximum Volume                                  |
|               |                       | Noise Gate                                      |
|               |                       | WaveTune™                                       |
| Outputs       | Туре                  | 4 x Stereo Balanced Line                        |
|               | Connector             | 4 x 3-pin Euro Terminal Block (Pitch - 3.81 mm) |
|               | Impedance             | 52 Ω  |
|               | Туре                  | Dante™/AES67 (4 channels)                       |
|               | Connector             | RJ45  |
|               | Configurable Settings | 8 Channels Mixer                                |
|               |                       | Gain  |
|               |                       | Maximum Volume                                  |
| Power         | Supply                | PoE powered (IEEE 802.3at)                      |
|               | Consumption           | 3.59 W  |
| Phantom power |                       | +48 V DC  |

# **Product Features:**

| Dimensions  |          | 108 x 44 x 165 mm (W x H x D)          |
|-------------|----------|--|
| Weight      |          | 0.48 kg                                |
| Accessories | Included | Bluetooth antenna                      |
|             | Optional | MBS1xx Optional Wall mounting brackets |

