Integrated 2-Channel Zone Amplifier (Audio Only)





The AU-A50 is a compact 2 channel digital zone amplifier that is perfect for providing high quality audio distribution into remote AV zones within any multi-room installation. This advanced solution can integrate digital and analogue audio signals from multiple sources, including an audio output from a TV, enabling sound reenforcement within any zone.

FEATURES

- · 30W per channel digital stereo Amplifier
- Control via remote control, RS-232 or IP (Web GUI or Telnet)
- · Single zone amplifier
- LCD Display
- Compact design for remote in-zone application



SPECIFICATIONS

Input: 1x RCA (1x Coaxial 2 Channel LPCM),

1x Toslink (1x Optical 2 Channel LPCM)
2x RCA (1x Analogue Stereo (L/R))
1x 3.5mm Stereo mini-jack (1x Analogue

Stereo(L/R))

1x RJ45 (1x IP Control)

1x RJ45 (1x Keypad - Reserved for future

use - Propriety Data)

1x 3.5mm Stereo mini-jack (1x Infra Red

Receiver)
1x USB Type A (1x Service Port Propriety

Data)

4x Speaker Binding Posts (1x Speaker

Level Stereo Output)

Power: 24V DC (US/EU standards,

CE/FCC/UL certified)

Dimensions: 215mm (W) x 150mm (D) x 50mm (H)

Gross Weight: 1680g
Net. Weight: 1380g
Packagina: Boxed

Output:



